

# M-Series Submaster Module



The M-Series Submaster Module provides the user with an additional 24 handles of controls for cuelists, channels, submasters or inhibitives. Combined with any M-Series consoles or the Martin M-PC, the Submaster Module makes it easy and relatively inexpensive to build a 24, 48 or even 96 fader desk - the perfect startup theater or busking console.

24 x playback faders with single-function button

5 x LCD navigation buttons with scroll wheel

2 x 40-character display for labeling

## GALLERY



## FEATURES

## TECHNICAL SPECIFICATIONS

### Physical

Length: 275 mm (10.9 in.)

Width: 483 mm (19.1 in.)

Height: 128 mm (5.1 in.)

Weight: 4.6 kg (10.2 lbs.)

### Control/User Interface

24 x non-motorized faders with single function button (every cueist type supported)

40-character display for labeling

5 x LCD navigation buttons with scroll wheel

### Connections

M-Series™ Module link USB: Neutrik locking RJ45 Ethercon sockets

USB input: USB device socket

USB devices: USB host socket

Desk lamp: 2.5 mm DC bayonet

AC power input: 3-pin IEC male socket

AC power throughput: 3-pin IEC female socket

### Electrical

AC power: 100-240 V nominal, 50/60 Hz

Power supply unit: Auto-ranging electronic switch-mode

Main fuse: 2 AT (slow blow)

Desk lamp output: 12 V

AC power output: Unswitched, unfused, max. 6 A

### Approvals

EU safety: EN 60950

EU EMC: EN 55022, EN 55024, EN 61000-3-2, EN 61000-3-3

US safety (pending): ANSI/UL 60950-1

Canadian safety (pending): CSA C22.2 No. 60950-1

### Included Items

1.5 m power cable, 3-pin IEC: P/N 11501012

Ethercon patch cable: P/N 11840144

USB cable: P/N 11840066

### Accessories

M-Series™ Empty Frame in Flightcase: P/N 90732120

### Ordering Information

M-Series™ Submaster Module (complete): P/N 90732170

